

Wiring description

Pin	4-pin socket						
1	U frequency converter phase						
2	V frequency converter phase						
3	W frequency converter phase						
4	Wiring ground						

GDK85-24Z/2.2-BJ

Rated power 2.2 kw Rated voltage 380V

Rated rotating speed 24000 r/min

Rated frequency 400 Hz
Rated current 5.5 A
ER nut ER-20

Bearing model 7005C×2 7002C×2/Steel ball

Bearing lubrication Grease lubrication

Weight 10 KG

Rotating mode anticlockwise from the shaft extension end

Special warning:

- 1. The electric main shaft shall be installed at the clamped position; otherwise the bearing will be easily damaged!
- The compressed air shall be dry and clean, and the filtering accuracy shall be 0.1 micron!
 Atmospheric pressure is 0.1- 0.2MPa, and the air seal shall be normally open. It is recommended to
 use the two-level filtration, with the filtration accuracy of 0.5 micron/0.1 micron respectively, and the
 air filter shall have automatic discharge device.

											380V
Marks Designe	Number of places	Zoning	Modified document number	Signature	Date						Outline
by	<u> </u>		by			Phase mark		Weight	Scale	diagram	
Reviewe	_										
by	۵										GDK85-24Z/2.2-BJ
Processe by	ed		Approved by			Total page(s)		Page			