



GDF60-18Z/6.0
 Power 6.0kw
 Voltage 380V
 Current 12.0A
 Frequency 300Hz
 Rotational speed 18000r/min

Weight:13KG
 ER Nut: ER32
 Cooling method: Air cooling
 Lubrication method of bearings:grease lubrication
 Angular contact ball bearing with high precision:
 2X7008C P4/2X7002C P4
 Rotation direction:Counterclockwise viewed from the
 shaft extension

Notice:It shall apply thread adhesive or spring washer to prevent
 loosening while mounting fastening screw!