



Wiring description

Pins	four-core socket
1	U-converter phase
2	V-converter phase
3	W-converter phase
4	Grounding wire \ominus

GDK85-24Z/2.2D

Rated power: 2.2Kw

Rated Voltage: 220V

Rated speed: 24000r/min

Rated frequency: 400Hz

Rated current: 7.6A

ER Nut: ER-20

Type of bearing: 7005CX2 7203CX2

bearing lubrication: grease lubrication

Weight: 8KG

Rotation direction: Counterclockwise
viewed from the shaft extension

Special warning:

1. The spindle shall be mounted to the clamping position; otherwise it would damage the bearing!
2. The power of the frequency converter must match the power of the electric spindle. If the power of the frequency converter is too small, the electric spindle will be weak or frequent trip protection.