



GDF46-18Z/2.2  
 Power 2.2kw  
 Voltage 220V  
 Current 7.8A  
 Frequency 300Hz  
 Rotational speed 18000r/min

Weight:7KG  
 ER Nut: ER20  
 Cooling method: Air cooling  
 Lubrication method of bearings:grease lubrication  
 Angular contact ball bearing with high precision:  
 2X7005C P4/1X6002V P5  
 Rotation direction:Counterclockwise viewed from the  
 shaft extension

Notice:It shall apply thread adhesive or spring washer to prevent  
 loosening while mounting fastening screw!